SLEPc: Scalable Library for Eigenvalue Problem Computations

Jose E. Roman

High Performance Networking and Computing Group (GRyCAP)
Universidad Politécnica de Valencia, Spain

August, 2004

Tutorial Outline

Introduction

Eigenproblems: Motivation

Large sparse eigenvalue problems are among the most demanding calculations in scientific computing

Example application areas:

- Dynamic structural analysis (e.g. civil engineering)
- Stability analysis (e.g. control engineering)
- Eigenfunction determination (e.g. quantum chemistry)
- Bifurcation analysis (e.g. fluid dynamics)
- Statistics / information retrieval (e.g. Google's PageRank)

SLEPc

Motivating Example 1: Nuclear Engineering

Modal analysis of nuclear reactor cores

Objectives:

- Improve safety
- Reduce operation costs

Lambda Modes Equation

$$\mathcal{L}\phi = \frac{1}{\lambda}\mathcal{M}\phi$$

Target: modes associated to largest λ

- Criticality (eigenvalues)
- Prediction of instabilities and transient analysis (eigenvectors)

SLEPc

Motivating Example 1: Nuclear Engineering

Modal analysis of nuclear reactor cores

Objectives:

- Improve safety
- Reduce operation costs

Lambda Modes Equation

$$\mathcal{L}\phi = \frac{1}{\lambda}\mathcal{M}\phi$$

Target: modes associated to largest λ

- Criticality (eigenvalues)
- Prediction of instabilities and transient analysis (eigenvectors)



SLEPc

Motivating Example 1: Nuclear Engineering (cont'd)

Discretized eigenproblem

$$\begin{bmatrix} L_{11} & 0 \\ -L_{21} & L_{22} \end{bmatrix} \begin{bmatrix} \psi_1 \\ \psi_2 \end{bmatrix} = \frac{1}{\lambda} \begin{bmatrix} M_{11} & M_{12} \\ 0 & 0 \end{bmatrix} \begin{bmatrix} \psi_1 \\ \psi_2 \end{bmatrix}$$

Can be restated as

$$L_{11}^{-1} \left(M_{11} + M_{12} L_{22}^{-1} L_{21} \right) \psi_1 = \lambda \psi_1$$

Notes:

- Standard eigenproblem
- Matrix should not be computed explicitly
- In some applications, many successive problems are solved

SLEPc

Motivating Example 1: Nuclear Engineering (cont'd)

Discretized eigenproblem

$$\begin{bmatrix} L_{11} & 0 \\ -L_{21} & L_{22} \end{bmatrix} \begin{bmatrix} \psi_1 \\ \psi_2 \end{bmatrix} = \frac{1}{\lambda} \begin{bmatrix} M_{11} & M_{12} \\ 0 & 0 \end{bmatrix} \begin{bmatrix} \psi_1 \\ \psi_2 \end{bmatrix}$$

Can be restated as

$$L_{11}^{-1} \left(M_{11} + M_{12} L_{22}^{-1} L_{21} \right) \psi_1 = \lambda \psi_1$$

Notes:

- Standard eigenproblem
- Matrix should not be computed explicitly
- In some applications, many successive problems are solved

SLEPc

Motivating Example 1: Nuclear Engineering (cont'd)

Discretized eigenproblem

$$\begin{bmatrix} L_{11} & 0 \\ -L_{21} & L_{22} \end{bmatrix} \begin{bmatrix} \psi_1 \\ \psi_2 \end{bmatrix} = \frac{1}{\lambda} \begin{bmatrix} M_{11} & M_{12} \\ 0 & 0 \end{bmatrix} \begin{bmatrix} \psi_1 \\ \psi_2 \end{bmatrix}$$

Can be restated as

$$L_{11}^{-1} \left(M_{11} + M_{12} L_{22}^{-1} L_{21} \right) \psi_1 = \lambda \psi_1$$

Notes:

- Standard eigenproblem
- Matrix should not be computed explicitly
- In some applications, many successive problems are solved

SLEPc

Motivating Example 2: Computational Electromagnetics

Objective: Analysis of resonant cavities

Source-free wave equations

$$\nabla \times (\hat{\mu}_r^{-1} \nabla \times \vec{E}) - \kappa_0^2 \hat{\varepsilon}_r \vec{E} = 0$$
$$\nabla \times (\hat{\varepsilon}_r^{-1} \nabla \times \vec{H}) - \kappa_0^2 \hat{\mu}_r \vec{H} = 0$$

Target: A few smallest nonzero eigenfrequencies

Discretization: 1^{st} order edge finite elements (tetrahedral)

$$Ax = \kappa_0^2 Bx$$ Generalized Eigenvalue Problem

- A and B are large and sparse, possibly complex
- A is (complex) symmetric and semi-positive definite
- B is (complex) symmetric and positive definite

SLEPc

Motivating Example 2: Computational Electromagnetics

Objective: Analysis of resonant cavities

Source-free wave equations

$$\nabla \times (\hat{\mu}_r^{-1} \nabla \times \vec{E}) - \kappa_0^2 \hat{\varepsilon}_r \vec{E} = 0$$
$$\nabla \times (\hat{\varepsilon}_r^{-1} \nabla \times \vec{H}) - \kappa_0^2 \hat{\mu}_r \vec{H} = 0$$

Target: A few smallest nonzero eigenfrequencies

Discretization: 1^{st} order edge finite elements (tetrahedral)

$$Ax = \kappa_0^2 Bx$$

Generalized Eigenvalue Problem

- A and B are large and sparse, possibly complex
- A is (complex) symmetric and semi-positive definite
- B is (complex) symmetric and positive definite

SLEPc

Motivating Example 2: Comp. Electromagnetics (cont'd)

Matrix A has a high-dimensional null space, $\mathcal{N}(A)$

- The problem $Ax = \kappa_0^2 Bx$ has many zero eigenvalues
- These eigenvalues should be avoided during computation

$$\underbrace{\lambda_1, \lambda_2, \ldots, \lambda_k}_{=0}, \underbrace{\lambda_{k+1}, \lambda_{k+2}}_{\text{Target}}, \ldots, \lambda_n$$

Eigenfunctions associated to 0 are irrotational electric fields, $\vec{E} = -\nabla\Phi$. This allows the computation of a basis of $\mathcal{N}(A)$

Constrained Eigenvalue Problem

$$\left.\begin{array}{l} Ax = \kappa_0^2 Bx \\ C^T Bx = 0 \end{array}\right\}$$

where the columns of C span $\mathcal{N}(A)$

SLEPc

Motivating Example 2: Comp. Electromagnetics (cont'd)

Matrix A has a high-dimensional null space, $\mathcal{N}(A)$

- The problem $Ax = \kappa_0^2 Bx$ has many zero eigenvalues
- These eigenvalues should be avoided during computation

$$\underbrace{\lambda_1, \lambda_2, \ldots, \lambda_k}_{=0}, \underbrace{\lambda_{k+1}, \lambda_{k+2}}_{\text{Target}}, \ldots, \lambda_n$$

Eigenfunctions associated to 0 are irrotational electric fields, $\vec{E} = -\nabla\Phi$. This allows the computation of a basis of $\mathcal{N}(A)$

Constrained Eigenvalue Problem

$$\left.\begin{array}{l} Ax = \kappa_0^2 Bx \\ C^T Bx = 0 \end{array}\right\}$$

where the columns of C span $\mathcal{N}(A)$

SLEPc

Facts Observed from the Examples

- Many formulations
  - Not all eigenproblems are formulated as simply $Ax = \lambda x$ or $Ax = \lambda Bx$
  - We have to account for: spectral transformations, block-structured problems, constrained problems, etc.
- Wanted solutions
  - Many ways of specifying which solutions must be sought
  - We have to account for: different extreme eigenvalues as well as interior ones
- Various problem characteristics
  - Problems can be real/complex, Hermitian/non-Hermitian

Goal: provide a uniform, coherent way of addressing these problems

Facts Observed from the Examples

- Many formulations
  - Not all eigenproblems are formulated as simply $Ax = \lambda x$ or $Ax = \lambda Bx$
  - We have to account for: spectral transformations, block-structured problems, constrained problems, etc.
- Wanted solutions
  - Many ways of specifying which solutions must be sought
  - We have to account for: different extreme eigenvalues as well as interior ones
- Various problem characteristics
  - Problems can be real/complex, Hermitian/non-Hermitian

Goal: provide a uniform, coherent way of addressing these problems

SLEPc

Facts Observed from the Examples

- Many formulations
  - Not all eigenproblems are formulated as simply $Ax = \lambda x$ or $Ax = \lambda Bx$
  - We have to account for: spectral transformations, block-structured problems, constrained problems, etc.
- Wanted solutions
  - Many ways of specifying which solutions must be sought
  - We have to account for: different extreme eigenvalues as well as interior ones
- Various problem characteristics
  - Problems can be real/complex, Hermitian/non-Hermitian

Goal: provide a uniform, coherent way of addressing these problems

SLEPc

Facts Observed from the Examples

- Many formulations
  - Not all eigenproblems are formulated as simply $Ax = \lambda x$ or $Ax = \lambda Bx$
  - We have to account for: spectral transformations, block-structured problems, constrained problems, etc.
- Wanted solutions
  - Many ways of specifying which solutions must be sought
  - We have to account for: different extreme eigenvalues as well as interior ones
- Various problem characteristics
  - Problems can be real/complex, Hermitian/non-Hermitian

Goal: provide a uniform, coherent way of addressing these problems

SLEPc

Background on Eigenvalue Problems

Consider the following eigenvalue problems

Standard Eigenproblem

$$Ax = \lambda x$$

Generalized Eigenproblem

$$Ax = \lambda Bx$$

where

- λ is a (complex) scalar: *eigenvalue*
- x is a (complex) vector: *eigenvector*
- Matrices A and B can be real or complex
- Matrices A and B can be symmetric (Hermitian) or not
- Typically, B is symmetric positive (semi-) definite

SLEPc

Solution of the Eigenvalue Problem

There are n eigenvalues (counted with their multiplicities)

Partial eigensolution: nev solutions

$$\lambda_0, \lambda_1, \ldots, \lambda_{nev-1} \in \mathbb{C}$$
$$x_0, x_1, \ldots, x_{nev-1} \in \mathbb{C}^n$$

nev = number of eigenvalues / eigenvectors (eigenpairs)

Different requirements:

- Compute a few of the dominant eigenvalues (largest magnitude)
- Compute a few λ_i's with smallest or largest real parts
- Compute all λ_i's in a certain region of the complex plane

SLEPc

Solution of the Eigenvalue Problem

There are n eigenvalues (counted with their multiplicities)

Partial eigensolution: nev solutions

$$\lambda_0, \lambda_1, \ldots, \lambda_{nev-1} \in \mathbb{C}$$
$$x_0, x_1, \ldots, x_{nev-1} \in \mathbb{C}^n$$

nev = number of eigenvalues / eigenvectors (eigenpairs)

Different requirements:

- Compute a few of the dominant eigenvalues (largest magnitude)
- Compute a few λ_i's with smallest or largest real parts
- Compute all λ_i's in a certain region of the complex plane

SLEPc

Single-Vector Methods

The following algorithm converges to the dominant eigenpair (λ_1, x_1), where $|\lambda_1| > |\lambda_2| \geq \cdots \geq |\lambda_n|$

Power Method

Set $y = v_0$
For $k = 1, 2, \ldots$
$v = y/\|y\|_2$
$y = Av$
$\theta = v^H y$
Check convergence
end

Notes:

- Only needs two vectors
- Deflation schemes to find subsequent eigenpairs
- Slow convergence (proportional to $|\lambda_1/\lambda_2|$)
- Fails if $|\lambda_1| = |\lambda_2|$

SLEPc

Single-Vector Methods

The following algorithm converges to the dominant eigenpair (λ_1, x_1), where $|\lambda_1| > |\lambda_2| \geq \cdots \geq |\lambda_n|$

Power Method

Set $y = v_0$
For $k = 1, 2, \ldots$
  $v = y/\|y\|_2$
  $y = Av$
  $\theta = v^H y$
  Check convergence
end

Notes:

- Only needs two vectors
- Deflation schemes to find subsequent eigenpairs
- Slow convergence (proportional to $|\lambda_1/\lambda_2|$)
- Fails if $|\lambda_1| = |\lambda_2|$

Variants of the Power Method

Shifted Power Method

- Example: Markov chain problem has two dominant eigenvalues $\lambda_1 = 1$, $\lambda_2 = -1$ $\Longrightarrow$ Power Method fails!
- Solution: Apply the Power Method to matrix $A + \sigma I$

Inverse Iteration

- Observation: The eigenvectors of A and A^{-1} are identical
- The Power Method on $(A - \sigma I)^{-1}$ will compute the eigenvalues closest to σ

Rayleigh Quotient Iteration (RQI)

- Similar to Inverse Iteration but updating σ in each iteration

Variants of the Power Method

Shifted Power Method

- Example: Markov chain problem has two dominant eigenvalues $\lambda_1 = 1$, $\lambda_2 = -1$ $\Longrightarrow$ Power Method fails!
- Solution: Apply the Power Method to matrix $A + \sigma I$

Inverse Iteration

- Observation: The eigenvectors of A and A^{-1} are identical
- The Power Method on $(A - \sigma I)^{-1}$ will compute the eigenvalues closest to σ

Rayleigh Quotient Iteration (RQI)

- Similar to Inverse Iteration but updating σ in each iteration

Variants of the Power Method

Shifted Power Method

- Example: Markov chain problem has two dominant eigenvalues $\lambda_1 = 1$, $\lambda_2 = -1$ $\Longrightarrow$ Power Method fails!
- Solution: Apply the Power Method to matrix $A + \sigma I$

Inverse Iteration

- Observation: The eigenvectors of A and A^{-1} are identical
- The Power Method on $(A - \sigma I)^{-1}$ will compute the eigenvalues closest to σ

Rayleigh Quotient Iteration (RQI)

- Similar to Inverse Iteration but updating σ in each iteration

SLEPc

Spectral Transformation

A general technique that can be used in many methods

$$Ax = \lambda x \quad \Longrightarrow \quad Tx = \theta x$$

In the transformed problem

- The eigenvectors are not altered
- The eigenvalues are modified by a simple relation
- Convergence is usually improved (better separation)

Shift of Origin	Shift-and-invert	Cayley
$T_S = A + \sigma I$	$T_{SI} = (A - \sigma I)^{-1}$	$T_C = (A - \sigma I)^{-1}(A + \tau I)$

Drawback: T not computed explicitly, linear solves instead

SLEPc

Spectral Transformation

A general technique that can be used in many methods

$$Ax = \lambda x \quad \Longrightarrow \quad Tx = \theta x$$

In the transformed problem

- The eigenvectors are not altered
- The eigenvalues are modified by a simple relation
- Convergence is usually improved (better separation)

Shift of Origin	Shift-and-invert	Cayley
$T_S = A + \sigma I$	$T_{SI} = (A - \sigma I)^{-1}$	$T_C = (A - \sigma I)^{-1}(A + \tau I)$

Drawback: T not computed explicitly, linear solves instead

SLEPc

Spectral Transformation

A general technique that can be used in many methods

$$Ax = \lambda x \quad \Longrightarrow \quad Tx = \theta x$$

In the transformed problem

- The eigenvectors are not altered
- The eigenvalues are modified by a simple relation
- Convergence is usually improved (better separation)

Shift of Origin	Shift-and-invert	Cayley
$T_S = A + \sigma I$	$T_{SI} = (A - \sigma I)^{-1}$	$T_C = (A - \sigma I)^{-1}(A + \tau I)$

Drawback: T not computed explicitly, linear solves instead

Invariant Subspace

A subspace $\mathcal{S}$ is called an *invariant subspace* of A if $A\mathcal{S} \subset \mathcal{S}$

- If $A \in \mathbb{C}^{n\times n}$, $V \in \mathbb{C}^{n\times k}$, and $H \in \mathbb{C}^{k\times k}$ satisfy

$$AV = VH$$

then $\mathcal{S} \equiv \mathcal{C}(V)$ is an invariant subspace of A

Objective: build an invariant subspace to extract the eigensolutions

Partial Schur Decomposition

$$AQ = QR$$

- Q has nev columns which are orthonormal
- R is a $nev \times nev$ upper (quasi-) triangular matrix

SLEPc

Invariant Subspace

A subspace $\mathcal{S}$ is called an *invariant subspace* of A if $A\mathcal{S} \subset \mathcal{S}$

- If $A \in \mathbb{C}^{n\times n}$, $V \in \mathbb{C}^{n\times k}$, and $H \in \mathbb{C}^{k\times k}$ satisfy

$$AV = VH$$

then $\mathcal{S} \equiv \mathcal{C}(V)$ is an invariant subspace of A

Objective: build an invariant subspace to extract the eigensolutions

Partial Schur Decomposition

$$AQ = QR$$

- Q has nev columns which are orthonormal
- R is a $nev \times nev$ upper (quasi-) triangular matrix

SLEPc

Projection Methods

The general scheme of a projection method:

1. Build an orthonormal basis of a certain subspace
2. Project the original problem onto this subspace
3. Use the solution of the projected problem to compute an approximate invariant subspace

- Different methods use different subspaces
  - Subspace Iteration: $A^k X$
  - Arnoldi, Lanczos: $\mathcal{K}_m(A, v_1) = \text{span}\{v_1, Av_1, \ldots, A^{m-1}v_1\}$
- Dimension of the subspace: ncv (number of column vectors)
- Restart & deflation necessary until nev solutions converged

SLEPc

Projection Methods

The general scheme of a projection method:

1. Build an orthonormal basis of a certain subspace
2. Project the original problem onto this subspace
3. Use the solution of the projected problem to compute an approximate invariant subspace

- Different methods use different subspaces
  - Subspace Iteration: $A^k X$
  - Arnoldi, Lanczos: $\mathcal{K}_m(A, v_1) = \text{span}\{v_1, Av_1, \ldots, A^{m-1}v_1\}$
- Dimension of the subspace: ncv (number of column vectors)
- Restart & deflation necessary until nev solutions converged

Summary

Observations to be added to the previous ones

- The solver computes only nev eigenpairs
- Internally, it works with ncv vectors
- Single-vector methods are very limited
- Projection methods are preferred
- Internally, solvers can be quite complex (deflation, restart, ...)
- Spectral transformations can be used irrespective of the solver
- Repeated linear solves may be required

Goal: hide eigensolver complexity and separate spectral transform

Summary

Observations to be added to the previous ones

- The solver computes only nev eigenpairs
- Internally, it works with ncv vectors
- Single-vector methods are very limited
- Projection methods are preferred
- Internally, solvers can be quite complex (deflation, restart, ...)
- Spectral transformations can be used irrespective of the solver
- Repeated linear solves may be required

Goal: hide eigensolver complexity and separate spectral transform

Basic Description

SLEPc

Executive Summary

SLEPc: Scalable Library for Eigenvalue Problem Computations

A *general* library for solving large-scale sparse eigenproblems on parallel computers

- For standard and generalized eigenproblems
- For real and complex arithmetic
- For Hermitian or non-Hermitian problems

Current version: 2.2.1 (released August 2004)

`http://www.grycap.upv.es/slepc`

SLEPc

SLEPc and PETSc

SLEPc extends PETSc for solving eigenvalue problems

PETSc: Portable, Extensible Toolkit for Scientific Computation

- Software for the solution of PDE's in parallel computers
- A freely available and supported research code
- Usable from C, C++, Fortran77/90
- Focus on abstraction, portability, interoperability, ...
- Object-oriented design (encapsulation, inheritance and polymorphism)
- Current: 2.2.1 `http://www.mcs.anl.gov/petsc`

SLEPc inherits all good properties of PETSc

Structure of SLEPc

SLEPc adds two new objects: EPS and ST

EPS: Eigenvalue Problem Solver

- The user specifies the problem via this object (entry point to SLEPc)
- Provides a collection of eigensolvers
- Allows the user to specify a number of parameters (e.g. which portion of the spectrum)

ST: Spectral Transformation

- Used to transform the original problem into $Tx = \theta x$
- Always associated to an EPS object, not used directly

Structure of SLEPc

SLEPc adds two new objects: EPS and ST

EPS: Eigenvalue Problem Solver

- The user specifies the problem via this object (entry point to SLEPc)
- Provides a collection of eigensolvers
- Allows the user to specify a number of parameters (e.g. which portion of the spectrum)

ST: Spectral Transformation

- Used to transform the original problem into $Tx = \theta x$
- Always associated to an EPS object, not used directly

Structure of SLEPc

SLEPc adds two new objects: EPS and ST

EPS: Eigenvalue Problem Solver

- The user specifies the problem via this object (entry point to SLEPc)
- Provides a collection of eigensolvers
- Allows the user to specify a number of parameters (e.g. which portion of the spectrum)

ST: Spectral Transformation

- Used to transform the original problem into $Tx = \theta x$
- Always associated to an EPS object, not used directly

SLEPc/PETSc Diagram



Basic Usage

Usual steps for solving an eigenvalue problem with SLEPc:

1. Create an EPS object
2. Define the eigenvalue problem
3. (Optionally) Specify options for the solution
4. Run the eigensolver
5. Retrieve the computed solution
6. Destroy the EPS object

All these operations are done via a generic interface, common to all the eigensolvers

SLEPc

Simple Example

```
EPS         eps;      /*  eigensolver context  */
Mat         A, B;     /*  matrices of Ax=kBx   */
Vec         xr, xi;   /*  eigenvector, x       */
PetscScalar kr, ki;   /*  eigenvalue, k        */

EPSCreate(PETSC_COMM_WORLD, &eps);
EPSSetOperators(eps, A, B);
EPSSetProblemType(eps, EPS_GNHEP);
EPSSetFromOptions(eps);

EPSSolve(eps);

EPSGetConverged(eps, &nconv);
for (i=0; i<nconv; i++) {
  EPSGetEigenpair(eps, i, &kr, &ki, xr, xi);
}

EPSDestroy(eps);
```

SLEPc

Simple Example

```
EPS         eps;      /*  eigensolver context  */
Mat         A, B;     /*  matrices of Ax=kBx   */
Vec         xr, xi;   /*  eigenvector, x       */
PetscScalar kr, ki;   /*  eigenvalue, k        */

EPSCreate(PETSC_COMM_WORLD, &eps);
EPSSetOperators(eps, A, B);
EPSSetProblemType(eps, EPS_GNHEP);
EPSSetFromOptions(eps);

EPSSolve(eps);

EPSGetConverged(eps, &nconv);
for (i=0; i<nconv; i++) {
  EPSGetEigenpair(eps, i, &kr, &ki, xr, xi);
}

EPSDestroy(eps);
```

SLEPc

Simple Example

```
EPS         eps;      /*  eigensolver context  */
Mat         A, B;     /*  matrices of Ax=kBx   */
Vec         xr, xi;   /*  eigenvector, x       */
PetscScalar kr, ki;   /*  eigenvalue, k        */

EPSCreate(PETSC_COMM_WORLD, &eps);
EPSSetOperators(eps, A, B);
EPSSetProblemType(eps, EPS_GNHEP);
EPSSetFromOptions(eps);

EPSSolve(eps);

EPSGetConverged(eps, &nconv);
for (i=0; i<nconv; i++) {
  EPSGetEigenpair(eps, i, &kr, &ki, xr, xi);
}

EPSDestroy(eps);
```

SLEPc

Simple Example

```
EPS         eps;      /*  eigensolver context  */
Mat         A, B;     /*  matrices of Ax=kBx   */
Vec         xr, xi;   /*  eigenvector, x       */
PetscScalar kr, ki;   /*  eigenvalue, k        */

EPSCreate(PETSC_COMM_WORLD, &eps);
EPSSetOperators(eps, A, B);
EPSSetProblemType(eps, EPS_GNHEP);
EPSSetFromOptions(eps);

EPSSolve(eps);

EPSGetConverged(eps, &nconv);
for (i=0; i<nconv; i++) {
  EPSGetEigenpair(eps, i, &kr, &ki, xr, xi);
}

EPSDestroy(eps);
```

SLEPc

Simple Example

```
EPS         eps;      /*  eigensolver context  */
Mat         A, B;     /*  matrices of Ax=kBx   */
Vec         xr, xi;   /*  eigenvector, x       */
PetscScalar kr, ki;   /*  eigenvalue, k        */

EPSCreate(PETSC_COMM_WORLD, &eps);
EPSSetOperators(eps, A, B);
EPSSetProblemType(eps, EPS_GNHEP);
EPSSetFromOptions(eps);

EPSSolve(eps);

EPSGetConverged(eps, &nconv);
for (i=0; i<nconv; i++) {
  EPSGetEigenpair(eps, i, &kr, &ki, xr, xi);
}

EPSDestroy(eps);
```

SLEPc

Details: Object Management

EPS is managed like any other PETSc object

`EPSCreate(MPI_Comm comm,EPS *eps)`

Creates a new instance

EPS is a "parallel" object:

- Parallel details are hidden from the programmer
- Many operations are collective

`EPSDestroy(EPS eps)`

Destroys the instance

Details: Object Management

EPS is managed like any other PETSc object

`EPSCreate(MPI_Comm comm,EPS *eps)`

Creates a new instance

EPS is a "parallel" object:

- Parallel details are hidden from the programmer
- Many operations are collective

`EPSDestroy(EPS eps)`

Destroys the instance

SLEPc

Details: Problem Definition

`EPSSetOperators(EPS eps, Mat A, Mat B)`

Used to pass the matrices that constitute the problem

- A generalized problem $Ax = \lambda Bx$ is specified by `A` and `B`
- For a standard problem $Ax = \lambda x$ set `B=PETSC_NULL`

`EPSSetProblemType(EPS eps,EPSProblemType type)`

Used to indicate the problem type

Problem Type	`EPSProblemType`	Command line key
Hermitian	`EPS_HEP`	`-eps_hermitian`
Generalized Hermitian	`EPS_GHEP`	`-eps_gen_hermitian`
Non-Hermitian	`EPS_NHEP`	`-eps_non_hermitian`
Generalized Non-Herm.	`EPS_GNHEP`	`-eps_gen_non_hermitian`

SLEPc

Details: Problem Definition

`EPSSetOperators(EPS eps, Mat A, Mat B)`

Used to pass the matrices that constitute the problem

- A generalized problem $Ax = \lambda Bx$ is specified by `A` and `B`
- For a standard problem $Ax = \lambda x$ set `B=PETSC_NULL`

`EPSSetProblemType(EPS eps,EPSProblemType type)`

Used to indicate the problem type

Problem Type	`EPSProblemType`	Command line key
Hermitian	`EPS_HEP`	`-eps_hermitian`
Generalized Hermitian	`EPS_GHEP`	`-eps_gen_hermitian`
Non-Hermitian	`EPS_NHEP`	`-eps_non_hermitian`
Generalized Non-Herm.	`EPS_GNHEP`	`-eps_gen_non_hermitian`

Details: Specification of Options

`EPSSetFromOptions(EPS eps)`

Looks in the command line for options related to EPS

For example, the following command line

```
% program -eps_hermitian
```

is equivalent to a call `EPSSetProblemType(eps,EPS_HEP)`

Other options have an associated function call

```
% program -eps_nev 6 -eps_tol 1e-8
```

`EPSView(EPS eps, PetscViewer viewer)`

Prints information about the object (equivalent to `-eps_view`)

Details: Specification of Options

`EPSSetFromOptions(EPS eps)`

Looks in the command line for options related to EPS

For example, the following command line

```
% program -eps_hermitian
```

is equivalent to a call `EPSSetProblemType(eps,EPS_HEP)`

Other options have an associated function call

```
% program -eps_nev 6 -eps_tol 1e-8
```

`EPSView(EPS eps, PetscViewer viewer)`

Prints information about the object (equivalent to `-eps_view`)

SLEPc

Details: Specification of Options

EPSSetFromOptions(EPS eps)

Looks in the command line for options related to EPS

For example, the following command line

```
% program -eps_hermitian
```

is equivalent to a call EPSSetProblemType(eps,EPS_HEP)

Other options have an associated function call

```
% program -eps_nev 6 -eps_tol 1e-8
```

EPSView(EPS eps, PetscViewer viewer)

Prints information about the object (equivalent to -eps_view)

SLEPc

Details: Solving the Problem

`EPSSolve(EPS eps)`

Launches the eigensolver

Currently available eigensolvers:

- Power Iteration with deflation. This includes:
  - Inverse Iteration
  - Rayleigh Quotient Iteration (RQI)
- Subspace Iteration with Rayleigh-Ritz projection and locking
- Arnoldi method with explicit restart and deflation

Also interfaces to external software such as ARPACK

SLEPc

Details: Getting the Solution

```
EPSGetConverged(EPS eps, int *nconv)
```

Returns the number of computed eigenpairs

The number of computed eigenpairs may differ from that requested

```
EPSGetEigenpair(EPS eps, int i, PetscScalar *kr,
                PetscScalar *ki, Vec xr, Vec xi)
```

Returns the i-th solution of the eigenproblem

- kr Real part of the eigenvalue
- ki Imaginary part of the eigenvalue
- xr Real part of the eigenvector
- xi Imaginary part of the eigenvector

The eigenvalues are ordered according to certain criterion

SLEPc

Details: Getting the Solution

```
EPSGetConverged(EPS eps, int *nconv)
```

Returns the number of computed eigenpairs

The number of computed eigenpairs may differ from that requested

```
EPSGetEigenpair(EPS eps, int i, PetscScalar *kr,
                PetscScalar *ki, Vec xr, Vec xi)
```

Returns the i-th solution of the eigenproblem

- kr Real part of the eigenvalue
- ki Imaginary part of the eigenvalue
- xr Real part of the eigenvector
- xi Imaginary part of the eigenvector

The eigenvalues are ordered according to certain criterion

SLEPc

Built-in Support Tools

- Monitoring convergence

  ```
  % program -eps_monitor
  ```

- Plotting computed eigenvalues

  ```
  % program -eps_plot_eigs
  ```

- Printing profiling information

  ```
  % program -log_summary
  ```

- Debugging

  ```
  % program -start_in_debugger
  ```



Further Details

Eigensolver Parameters

EPSSetDimensions(EPS eps, int nev, int ncv)

- nev: Number of requested eigenvalues (-eps_nev)
- ncv: Number of column vectors (i.e. largest dimension of the working subspace) (-eps_ncv)

- One may let SLEPc decide the value of ncv
- Typically, $ncv > 2 \cdot nev$, even larger if possible

EPSSetTolerances(EPS eps, PetscReal tol, int max_it)

- tol: Tolerance for the convergence criterion (-eps_tol)
- max_it: Maximum number of iterations (-eps_max_it)

Eigensolver Parameters

EPSSetDimensions(EPS eps, int nev, int ncv)

- nev: Number of requested eigenvalues (-eps_nev)
- ncv: Number of column vectors (i.e. largest dimension of the working subspace) (-eps_ncv)

- One may let SLEPc decide the value of ncv
- Typically, $ncv > 2 \cdot nev$, even larger if possible

EPSSetTolerances(EPS eps, PetscReal tol, int max_it)

- tol: Tolerance for the convergence criterion (-eps_tol)
- max_it: Maximum number of iterations (-eps_max_it)

SLEPc

Changing the Eigensolver

EPSSetType(EPS eps,EPSType type)

Used to specify the solution algorithm

Method	EPSType	-eps_type
Dense (LAPACK)	EPSLAPACK	lapack
Power / Inverse / RQI	EPSPOWER	power
Subspace Iteration	EPSSUBSPACE	subspace
Arnoldi Method	EPSARNOLDI	arnoldi
Interface to ARPACK	EPSARPACK	arpack
Interface to BLZPACK	EPSBLZPACK	blzpack
Interface to PLANSO	EPSPLANSO	planso
Interface to TRLAN	EPSTRLAN	trlan

Selecting the Portion of the Spectrum

EPSSetWhichEigenpairs(EPS eps, EPSWhich which)

Specifies which part of the spectrum is requested

which	Command line key	Sorting criterion
EPS_LARGEST_MAGNITUDE	-eps_largest_magnitude	Largest $\|\lambda\|$
EPS_SMALLEST_MAGNITUDE	-eps_smallest_magnitude	Smallest $\|\lambda\|$
EPS_LARGEST_REAL	-eps_largest_real	Largest $\mathrm{Re}(\lambda)$
EPS_SMALLEST_REAL	-eps_smallest_real	Smallest $\mathrm{Re}(\lambda)$
EPS_LARGEST_IMAGINARY	-eps_largest_imaginary	Largest $\mathrm{Im}(\lambda)$
EPS_SMALLEST_IMAGINARY	-eps_smallest_imaginary	Smallest $\mathrm{Im}(\lambda)$

- Eigenvalues are sought according to this criterion (not all possibilities available for all solvers)
- Computed eigenvalues are sorted according to this criterion

SLEPc

Run-Time Examples

```
% program -eps_view -eps_monitor

% program -eps_type power -eps_nev 6 -eps_ncv 24

% program -eps_type arnoldi -eps_tol 1e-8 -eps_max_it 2000

% program -eps_type subspace -eps_hermitian -log_summary

% program -eps_type lapack

% program -eps_type arpack -eps_plot_eigs -draw_pause -1

% program -eps_type blzpack -eps_smallest_real
```

Some Utilities

`EPSSetInitialVector(EPS eps,Vec v0)`

Sets the initial vector used to build the projection subspace

- Should be rich in the directions of wanted eigenvectors
- If no initial vector is provided, a random vector is used

`EPSComputeRelativeError(EPS eps,int j,PetscReal *err)`

Returns the relative error associated to the j-th solution

$$\frac{\|Ax_j - \lambda_j Bx_j\|}{\|\lambda_j x_j\|}$$

If $\lambda_j \simeq 0$ then it is computed as $\|Ax_j\|/\|x_j\|$

SLEPc

Some Utilities

`EPSSetInitialVector(EPS eps,Vec v0)`

Sets the initial vector used to build the projection subspace

- Should be rich in the directions of wanted eigenvectors
- If no initial vector is provided, a random vector is used

`EPSComputeRelativeError(EPS eps,int j,PetscReal *err)`

Returns the relative error associated to the j-th solution

$$\frac{\|Ax_j - \lambda_j Bx_j\|}{\|\lambda_j x_j\|}$$

If $\lambda_j \simeq 0$ then it is computed as $\|Ax_j\|/\|x_j\|$

SLEPc

Spectral Transformation in SLEPc

An ST object is always associated to any EPS object

$$Ax = \lambda x \quad \Longrightarrow \quad Tx = \theta x$$

- The user need not manage the ST object directly
- Internally, the eigensolver works with the operator T
- At the end, eigenvalues are transformed back automatically

ST	Standard problem	Generalized problem
`shift`	$A + \sigma I$	$B^{-1}A + \sigma I$
`sinvert`	$(A - \sigma I)^{-1}$	$(A - \sigma B)^{-1}B$
`cayley`	$(A - \sigma I)^{-1}(A + \tau I)$	$(A - \sigma B)^{-1}(A + \tau B)$

SLEPc

Spectral Transformation in SLEPc

An ST object is always associated to any EPS object

$$Ax = \lambda x \quad \Longrightarrow \quad Tx = \theta x$$

- The user need not manage the ST object directly
- Internally, the eigensolver works with the operator T
- At the end, eigenvalues are transformed back automatically

ST	Standard problem	Generalized problem
`shift`	$A + \sigma I$	$B^{-1}A + \sigma I$
`sinvert`	$(A - \sigma I)^{-1}$	$(A - \sigma B)^{-1}B$
`cayley`	$(A - \sigma I)^{-1}(A + \tau I)$	$(A - \sigma B)^{-1}(A + \tau B)$

SLEPc

Spectral Transformation in SLEPc

An ST object is always associated to any EPS object

$$Ax = \lambda x \quad \Longrightarrow \quad Tx = \theta x$$

- The user need not manage the ST object directly
- Internally, the eigensolver works with the operator T
- At the end, eigenvalues are transformed back automatically

ST	Standard problem	Generalized problem
`shift`	$A + \sigma I$	$B^{-1}A + \sigma I$
`sinvert`	$(A - \sigma I)^{-1}$	$(A - \sigma B)^{-1}B$
`cayley`	$(A - \sigma I)^{-1}(A + \tau I)$	$(A - \sigma B)^{-1}(A + \tau B)$

SLEPc

Defining the Spectral Transform

`STSetType(ST st,STType type)`

For setting the type of spectral transformation

Spectral Transform	`type`	`-st_type`	Operator
Shift of origin	`STSHIFT`	`shift`	$B^{-1}A + \sigma I$
Shift-and-invert	`STSINV`	`sinvert`	$(A - \sigma B)^{-1}B$
Cayley	`STCAYLEY`	`cayley`	$(A - \sigma B)^{-1}(A + \tau B)$

The default is shift of origin with a value of $\sigma = 0$

`STSetShift(ST st,PetscScalar shift)`

Used to provide the value of the shift σ (`-st_shift`)

There is an analogous function for setting the value of τ

SLEPc

Defining the Spectral Transform

STSetType(ST st,STType type)

For setting the type of spectral transformation

Spectral Transform	type	-st_type	Operator
Shift of origin	STSHIFT	shift	$B^{-1}A+\sigma I$
Shift-and-invert	STSINV	sinvert	$(A-\sigma B)^{-1}B$
Cayley	STCAYLEY	cayley	$(A-\sigma B)^{-1}(A+\tau B)$

The default is shift of origin with a value of $\sigma = 0$

STSetShift(ST st,PetscScalar shift)

Used to provide the value of the shift σ (-st_shift)

There is an analogous function for setting the value of τ

Accessing the ST Object

The user does not create the ST object

`EPSGetST(EPS eps, ST *st)`

Gets the ST object associated to an EPS

Necessary for setting options in the source code

Linear Solves. All operators contain an inverse (except $B^{-1}A + \sigma I$ in the case of a standard problem)

- Linear solves are handled internally via a KSP object

`STGetKSP(ST st, KSP *ksp)`

Gets the KSP object associated to an ST

All KSP options are available, by prepending the `-st_` prefix

Accessing the ST Object

The user does not create the ST object

`EPSGetST(EPS eps, ST *st)`

Gets the ST object associated to an EPS

Necessary for setting options in the source code

Linear Solves. All operators contain an inverse (except $B^{-1}A + \sigma I$ in the case of a standard problem)

- Linear solves are handled internally via a KSP object

`STGetKSP(ST st, KSP *ksp)`

Gets the KSP object associated to an ST

All KSP options are available, by prepending the `-st_` prefix

SLEPc

More Run-Time Examples

```
% program -eps_type power -st_type shift -st_shift 1.5

% program -eps_type power -st_type sinvert -st_shift 1.5

% program -eps_type power -st_type sinvert
          -eps_power_shift_type rayleigh

% program -eps_type arpack -eps_tol 1e-6
          -st_type sinvert -st_shift 1
          -st_ksp_type cgs -st_ksp_rtol 1e-8
          -st_pc_type sor  -st_pc_sor_omega 1.3
```

Advanced Features

SLEPc

Coefficient Matrix of Linear Systems

STSetMatMode(ST st, STMatMode mode)

Allows to modify the way in which the matrix $A - \sigma B$ is created

mode	-st_matmode	Description
STMATMODE_COPY	copy	Creates a copy (default)
STMATMODE_INPLACE	inplace	Overwrites matrix A
STMATMODE_SHELL	shell	Uses a *shell* matrix

STSetMatStructure(ST st, MatStructure str)

To indicate whether matrices A and B have the same nonzero structure or not

Coefficient Matrix of Linear Systems

STSetMatMode(ST st, STMatMode mode)

Allows to modify the way in which the matrix $A - \sigma B$ is created

mode	-st_matmode	Description
STMATMODE_COPY	copy	Creates a copy (default)
STMATMODE_INPLACE	inplace	Overwrites matrix A
STMATMODE_SHELL	shell	Uses a *shell* matrix

STSetMatStructure(ST st, MatStructure str)

To indicate whether matrices A and B have the same nonzero structure or not

SLEPc

Orthogonalization in SLEPc

Gram-Schmidt with Iterative Refinement. Parameter η controls the frequency of reorthogonalizations

Classical Gram-Schmidt

$$
\begin{aligned}
&h = Q^H v \\
&\tilde{q} = v - Qh \\
&\text{If } ||\tilde{q}||_2 < \eta ||h||_2 \\
&\quad s = Q^H \tilde{q} \\
&\quad \tilde{q} = \tilde{q} - Qs \\
&\quad h = h + s \\
&\text{End} \\
&q = \tilde{q}/||\tilde{q}||_2
\end{aligned}
$$

Modified Gram-Schmidt

$$
\begin{aligned}
&\tilde{q} = v \\
&\text{For } i = 1, \ldots, m \\
&\quad h_i = q_i^H \tilde{q} \\
&\quad \tilde{q} = \tilde{q} - q_i h_i \\
&\text{End} \\
&\text{If } ||\tilde{q}||_2 < \eta ||h||_2 \\
&\quad \text{For } i = 1, \ldots, m \\
&\quad\quad s_i = q_i^H \tilde{q} \\
&\quad\quad \tilde{q} = \tilde{q} - q_i s_i \\
&\quad \text{End} \\
&\quad h = h + s \\
&\text{End} \\
&q = \tilde{q}/||\tilde{q}||_2
\end{aligned}
$$

SLEPc

Changing the Orthogonalization Method

```
EPSSetOrthogonalization(EPS eps,
        EPSOrthogonalizationType type,
        EPSOrthogonalizationRefinementType refinement,
        PetscReal eta)
```

Specifies the orthogonalization method and its parameters

type	-eps_orthog_type	Orthogonalization
EPS_CGS_ORTH	cgs	Classical Gram-Schmidt
EPS_MGS_ORTH	mgs	Modified Gram-Schmidt

refinement	-eps_orthog_refinement	Refinement
EPS_ORTH_REFINE_NEVER	never	No reorthogonalization
EPS_ORTH_REFINE_ALWAYS	always	Two iterations
EPS_ORTH_REFINE_IFNEEDED	ifneeded	Depends on parameter η -eps_orthog_eta

SLEPc

Preserving the Symmetry

In the case of generalized eigenproblems in which both A and B are symmetric, symmetry is lost because none of $B^{-1}A+\sigma I$, $(A-\sigma B)^{-1}B$ or $(A-\sigma B)^{-1}(A+\tau B)$ is symmetric

Choice of Inner Product

- Standard Hermitian inner product: $\langle x,y\rangle = x^H y$
- B-inner product: $\langle x,y\rangle_B = x^H B\, y$

Observations:

- $\langle x,y\rangle_B$ is a genuine inner product only if B is symmetric positive definite
- $\mathbb{R}^n$ with $\langle x,y\rangle_B$ is isomorphic to the Euclidean n-space $\mathbb{R}^n$ with the standard Hermitian inner product
- $B^{-1}A$ is auto-adjoint with respect to $\langle x,y\rangle_B$

Preserving the Symmetry

In the case of generalized eigenproblems in which both A and B are symmetric, symmetry is lost because none of $B^{-1}A+\sigma I$, $(A-\sigma B)^{-1}B$ or $(A-\sigma B)^{-1}(A+\tau B)$ is symmetric

Choice of Inner Product

- Standard Hermitian inner product: $\langle x,y\rangle = x^H y$
- B-inner product: $\langle x,y\rangle_B = x^H B\, y$

Observations:

- $\langle x,y\rangle_B$ is a genuine inner product only if B is symmetric positive definite
- $\mathbb{R}^n$ with $\langle x,y\rangle_B$ is isomorphic to the Euclidean n-space $\mathbb{R}^n$ with the standard Hermitian inner product
- $B^{-1}A$ is auto-adjoint with respect to $\langle x,y\rangle_B$

SLEPc

Preserving the Symmetry

In the case of generalized eigenproblems in which both A and B are symmetric, symmetry is lost because none of $B^{-1}A+\sigma I$, $(A-\sigma B)^{-1}B$ or $(A-\sigma B)^{-1}(A+\tau B)$ is symmetric

Choice of Inner Product

- Standard Hermitian inner product: $\langle x,y\rangle = x^H y$
- B-inner product: $\langle x,y\rangle_B = x^H B\, y$

Observations:

- $\langle x,y\rangle_B$ is a genuine inner product only if B is symmetric positive definite
- $\mathbb{R}^n$ with $\langle x,y\rangle_B$ is isomorphic to the Euclidean n-space $\mathbb{R}^n$ with the standard Hermitian inner product
- $B^{-1}A$ is auto-adjoint with respect to $\langle x,y\rangle_B$

SLEPc

SLEPc Abstraction



These operations are virtual functions: STInnerProduct and STApply

SLEPc

SLEPc Abstraction



These operations are virtual functions: STInnerProduct and STApply

Deflation Subspaces

EPSAttachDeflationSpace(EPS eps,int n,Vec *ds,PetscTruth ortho)

Allows to provide a basis of a deflating subspace $\mathcal{S}$

The eigensolver works with the restriction of the problem to the orthogonal complement of this subspace $\mathcal{S}$

Possible uses:

- When $\mathcal{S}$ is an invariant subspace, then the corresponding eigenpairs are not computed again
- If $\mathcal{S}$ is the null space of the operator, then zero eigenvalues are skipped
- In general, for constrained eigenvalue problems
- Also for singular pencils (A and B share a common null space)

Deflation Subspaces

EPSAttachDeflationSpace(EPS eps,int n,Vec *ds,PetscTruth ortho)

Allows to provide a basis of a deflating subspace $\mathcal{S}$

The eigensolver works with the restriction of the problem to the orthogonal complement of this subspace $\mathcal{S}$

Possible uses:

- When $\mathcal{S}$ is an invariant subspace, then the corresponding eigenpairs are not computed again
- If $\mathcal{S}$ is the null space of the operator, then zero eigenvalues are skipped
- In general, for constrained eigenvalue problems
- Also for singular pencils (A and B share a common null space)

Concluding Remarks

SLEPc

Highlights

- Growing number of eigensolvers
- Seamlessly integrated spectral transformation
- Easy programming with PETSc's object-oriented style
- Data-structure neutral implementation
- Run-time flexibility, giving full control over the solution process
- Portability to a wide range of parallel platforms
- Usable from code written in C, C++ and Fortran
- Extensive documentation

SLEPc

Future Directions

Short Term

- Lanczos method with different reorthogonalization strategies
- Davidson method

Mid Term

- Implicitly Restarted Arnoldi method
- Support for a series of closely related problems

Longer Term

- Jacobi-Davidson method
- Block versions of some eigensolvers
- Enable computational intervals in some eigensolvers

Notice to Users

Help us improve SLEPc!

Want to hear about:

- New features you would like to see
- Bugs or portability problems
- Request for project collaboration

Contact us: `slepc-maint@grycap.upv.es`

Thanks!

http://www.grycap.upv.es/slepc

slepc-maint@grycap.upv.es